

TEMU

GRLIB GPTIMER Device Model Manual

Mattias Holm

Version 1.1, 2016-05-12

Table of Contents

1. Introduction

2. Configuration

2.1. Separate Interrupts

2.2. Interrupt Index

2.3. Number of Timers

2.4. Clear IRQ on Set

3. Attributes

3.1. Properties

3.2. Interfaces

3.3. Ports

4. Limitations

1

1

1

1

1

1

1

1

2

3

3

Table 1. Record of Changes

Rev	Date	Author	Note
1.1	2016-05-12	MH	Auto gen tables.
1.0	2015-03-01	MH	Initial version.

1. Introduction

The GPTIMER is part of the GRLIB device library from Gaisler. The timer runs using synchronised events in order to ensure that would a timer tick be broadcasted by the interrupt controller, then the IRQ should be taken at roughly the same time.

2. Configuration

2.1. Separate Interrupts

Set the "config.separateInterrupts" property to non-zero.

2.2. Interrupt Index

The interrupt number can be set by configuring the "pnp.config" property. The lower 5 bits of the property is used for this.

2.3. Number of Timers

Set the "config.numTimers" property. By default this value is 4 to be compatible with the UT699.

2.4. Clear IRQ on Set

Set the "config.clearIrqOnSet" property changes the behaviour of bit 4 in the timer control registers. ClearOnSet can be non-zero (the default), in that case writing a 1 to the bit will clear bit 4 (i.e. it will read out as 0), if clearOnSet is zero, the bit is cleared if bit 4 is 0 in the written word.

The reason for this are ambiguities in the LEON3 and UT699 manuals.

3. Attributes

3.1. Properties

Name	Type	Description
config.clearIrqOnSet	uint8_t	Use behaviour in GRIP manual. Set to zero for beahviour as documented in (UT699 manual from 2012 (p77)).
config.clockDivider	uint32_t	Clock divider for scaling event posting
config.irqNumber	uint8_t	Set interrupt number for first interrupt
config.numTimers	uint8_t	
config.separateInterrupts	uint8_t	Enable separate interrupts
config.traceReads	uint8_t	
config.traceWrites	uint8_t	
configReg	uint32_t	
control	[7 x uint32_t]	
counters	[7 x uint32_t]	
irqCtrl	iref / <unknown>	
object.timeSource	object	Time source object (a cpu or machine object)
pnnp.bar	uint32_t	
pnnp.config	uint32_t	
reload	[7 x uint32_t]	
scaler	uint32_t	
scalerReload	uint32_t	

3.2. Interfaces

Name	Type	Description
ApbIface	ApbIface	
DeviceIface	DeviceIface	
MemAccessIface	MemAccessIface	
ObjectIface	ObjectIface	
ResetIface	ResetIface	

3.3. Ports

Prop	Iface	Description
-	-	-

4. Limitations

The following deviations from real hardware are known to exist with this model:

- The Disable Timer Freeze bit is always 1 and cannot be configured.
- The Debug Halt bit for each timer is always 0 and cannot be altered.
- Chained timers are not supported at the moment.
- The last timer does not work as a watchdog.
- As the timer utilise synchronised events, the minimum time for a timer expiration on a multi-core CPU would be equal to the time-quanta that the machine has been configured with.